



## INTRODUCTION TO COMPUTERS II MODULE 2

### Basic problems:

1. Indicate the result of executing the following instructions in RISC-V, providing the final content of the registers and the memory positions.

- |                                   |                                |
|-----------------------------------|--------------------------------|
| a) <code>add x1, x1, x2</code>    | g) <code>add x2, x0, x4</code> |
| b) <code>addi x3, x2, 2</code>    | h) <code>lw x1, 0(x4)</code>   |
| c) <code>sub x4, x3, x0</code>    | i) <code>lw x2, 4(x5)</code>   |
| d) <code>andi x2, x3, 0xf0</code> | j) <code>and x5, x1, x3</code> |
| e) <code>sll x4, x2, x5</code>    | k) <code>sw x3, 0(x5)</code>   |
| f) <code>or x1, x1, x2</code>     | l) <code>sw x4, 4(x4)</code>   |

Assume that, for each instruction, the initial content of the registers and the memory positions is the following:

| Registers |            |
|-----------|------------|
| x1        | 0x00000016 |
| x2        | 0x00000054 |
| x3        | 0xffffffff |
| x4        | 0x00000000 |
| x5        | 0x00000004 |

| Memory |            |
|--------|------------|
| 0x00   | 0x03393826 |
| 0x04   | 0xea0063af |
| 0x08   | 0x17fa8912 |
| 0x0C   | 0xbc983304 |
| 0x10   | 0x7845f34a |
| 0x14   | 0x534b4aaa |

### Additional problems:

2. Explain why the following instructions are not valid:

```
addi x3, 3, x2
add x3, x2, 0(x1)
beq x3, 0, 8
beq x3, x2, 3
slli x3, x3, 40
muli x3, x2, 28
lw x8, -4000(x1)
```

3. The following constants are placed in memory, starting at position 0x1000:

- 0x10203040 word
- 0x50 byte
- 0x6070 half word
- 0x80 byte
- 0x90a0b0e0 word

Assuming that they are placed in the given order, taking the minimum space possible and following the RISC-V alignment and organization, provide:

- The initial address of each one.
- The value of the byte contained in these addresses: 0x1001, 0x1006 y 0x100c.
- The percentage of wasted memory.

- d) An alternate order to reduce the required memory as much as possible.
4. Assuming that register x7 contains address 0x10000000 and that the word data 0x1020d040 is located in such address, indicate the word that is stored in address 0x10000004 after executing the following pairs of instructions:
- a) `lb x6, 0(x7)`                      b) `lh x6, 0(x7)`                      c) `lhu x6, 0(x7)`  
`sw x6, 4(x7)`                              `sw x6, 4(x7)`                              `sw x6, 4(x7)`
5. Write the instruction/s needed to load the following constants into register x10:
- 0xabc
  - 0x1abc
  - 0x12345678
  - 0x56789abc